

How to integrate a Galaxy Dimension intrusion panel with OnGuard

Last Modified on 06/05/2025 11:21 am EDT

How to integrate a Galaxy Dimension intrusion panel with OnGuard

Procedure Steps

- 1) Spy key version 5.56 must be applied to the Galaxy Dimension panel, to configure it as a G3 panel. The spy key can be obtained from Honeywell. Note that each spy key is unique, so each time this step is done, a new spy key must be obtained.
- 2) In the Galaxy Dimension panel configuration, select option 56 for **Communications**.
- 3) Select option 6 for **RS232**.
- 4) Change the mode to **Direct**.
- 5) Select option 2 for **Format**, and select **Microtech**.
- 6) Enable custom zones and all other options in step 5.

Once the Galaxy Dimension panel is online, all zones, areas and users can be created in OnGuard. Refer to the *Intrusion Detection User Guide* for more information.

Applies To

OnGuard 2009 (6.3.249) or later
Galaxy Dimension intrusion panels

Additional Information

None
