

How to perform an event configuration flush in System Administration for IntelligentVideo

Last Modified on 05/22/2025 9:40 am EDT

How to perform an event configuration flush in System Administration for IntelligentVideo

Procedure Steps

- 1) In System Administration, open the IntelligentVideo screen from the **Video menu > IntelligentVideo...**
- 2) Select the **IntelligentVideo Events** tab.
- 3) Select (place a check mark beside) the appropriate camera channel, then click [Modify].
- 4) Select the camera icon located in the lower right side of the Event Type list to open the **Event Configuration/Search** screen.
- 5) Change any parameter in the **Event Configuration/Search** screen to a different value, then click [OK].
- 6) Click [OK] to save the change to the camera channel, then click [Modify].
- 7) Select the camera icon located in the lower right side of the Event Type list to open the **Event Configuration/Search** screen again.
- 8) Change the parameter modified in step 5 back to its original value, then click [OK].
- 9) Click [OK] to save the change to the camera channel.

At this time, the event configuration flush is complete.

Applies To

OnGuard (All versions)
IntelligentVideo (All versions)

Additional Information

None

