How to connect Brother Printer model QL-720NW to Visitor Self Service

Last Modified on 03/31/2025 12:42 pm EDT

Procedure Steps

- 1. Connect the Brother printer to a networked computer using the USB port.
- 2. Configure the Brother printer:
 - a. Brother Printer Setting Tool
 - b. Communication Settings
 - c. Wired LAN:
 - 1. IP Address:
 - Boot Method: Static
 - IP Address: 10.112.7.49
 - Subnet Mask: 255.255.255.224
 - Gateway: 10.112.7.33
 - 2. DNS Server:
 - Primary DNS Server IP Address: 159.82.80.7
 - Secondary DNS Server IP Address: 159.82.216.178
- 3. Click [Apply].

For example:

Communication Settings - Wired LAN > TC File Tools Help	CP/IP(Wired)	×
Printer: Brother QL-720NW	Vired LAN Node Nam Wireless LAN Node N	ne: BRN008077577032 ame: BRW008092D7DF29
General Wired LAN Wireless LAN		
Current Status Current Status TCP/IP(Wired)	Specify the TCP/IP settings used v IP Address Boot Method: IP Addr <u>e</u> ss: Subnet <u>M</u> ask: <u>G</u> ateway: DNS Server DNS Server DNS Server Method: Primary DNS Server IP Address:	STATIC ~ 10 . 112 . 7 . 49 255 . 255 . 224 10 . 112 . 7 . 33
	Secondary DNS Server IP Address	s: <u>159 . 82 . 216 . 178</u>
		Apply 🗸 Exit

- 4. Disconnect the printer from the computer's USB port and make sure the WiFi printer setting is OFF.
- 5. Confirm that the Brother printer is on the network.
 - a. Type the IP address into an Internet browser using a network-connected device.
 - b. Connect an iPad with VSS installed to the network via WiFi.
 - c. Open the VSS application on the iPad.
 - d. Tap on the printer URL (**Connections > Badge Printing > Printer URL**).
 - e. Enter **ipp://IPADDRESS:631/ipp/print** For example:





Visitor Self Service