

How to wire a L1 4G reader for enrollment over RS-232 instead of USB

Last Modified on 06/02/2025 5:04 pm EDT

How to wire a L1 4G reader for enrollment over RS-232 instead of USB

Procedure Steps

1. For RS-232 installations, a female DB9 connector should be used on the cable. 2. Connect RS232_TX (Violet wire - Pin 4 of 28) to the DB9 - Pin 2. 3. Connect RS232_RX (Violet/White wire - Pin 2 of 28) to the DB9 - Pin 3. 4. Connect Signal Ground (Black / Red wire - Pin 6 of 28) to the DB9 - Pin 5.

Applies To

OnGuard (All versions)

Additional Information
